

MX3000R

3.5KVA PETROL GENERATOR

4 STAGE DIGITAL METER | AUTOMATIC VOLTAGE REGULATOR
SUPERIOR QUALITY SENCI ALTERNATOR

- > 4 Stage Digital Meter Display
- > Automatic Voltage Regulator
- > Low Oil Alert Sensor
- > Superior Quality SENCI Alternator
- > 15L Capacity Fuel Tank
- > Large Muffler Design to reduce Noise
- > Heavy Duty 25mm Frame



Voltage (V)	240V
Amperage (A)	10.4A
Displacement (cc)	208cc
Fuel Tank Capacity (L)	15L
Rated Power (Watts)	3.1kVA/2500W
Max. Power (Watts)	3.5kVA/2800W

Noise Level (dB's) at 7m	77
Weight (Net)	48kg
Ignition	Manual/Recoil
Rated Frequency	50Hz
Cont. Running Time @50% Load	9 hrs
Cont. Running Time @100% Load	6.5 hrs

2
YEAR
WARRANTY