



Powering the Nation Since 1936



SPECIFICATIONS

MODEL	DGUH2.3S-2
POWER RATING	2.8 kVA @ 0.8 pf
ENGINE	Honda GP200
STARTING SYSTEM	Recoil
FUEL TANK	3.1 Litres
OPERATION HOURS	2.32 hrs @ 80% Load
FUEL TYPE	Petrol
DRY WEIGHT	40 kg
DIMENSION (LxWxH)	650 x 460 x 415 mm
NOISE LEVEL	67 dBA @ 7m

DGUH2.3S-2

2.8 kVA Honda Powered Generator

This small but powerful petrol generator is perfect for all your small power tools. Lightweight & durable, it'll make light work of even the trickiest of jobs.

Features:

- Reliable Honda GP200 engine
- 2 x 15 Amp outlet
- Heavy duty frame
- NSM brushless alternator



Specifications and product availability subject to variation without notice.

POWERED by
HONDA™

Victoria: Head Office

59 Export Drive
Brooklyn VIC 3012
P: +61 3 9316 9799
F: +61 3 9314 0909
E: dunlite@wellcross.com.au

New South Wales

Unit 2/1040 Canley Vale Road
Wetherill Park NSW 2164
P: +61 2 9757 5800
F: +61 2 9757 5899
E: nsw@wellcross.com.au

Queensland

Unit 2/55 Christensen Rd
Stapylton QLD 4207
P: +61 7 3386 2400
F: +61 7 3386 1241
E: qld@wellcross.com.au

North Queensland

Unit 19/547 Industry Park
547-593 Woolcock St
Mount Louisa, Townsville, QLD 4814
P: +61 7 4774 6331
E: nthqld@wellcross.com.au

Western Australia

Unit 8/235 Camboon Road
Malaga WA 6090
P: +61 8 9248 2955
F: +61 8 9248 2933
E: wa@wellcross.com.au

South Australia

Ph: 0417 592 530
E: bnicholas@wellcross.com.au

dunlite.com.au

07 5500 6027