


Smart efficient power anywhere.

Lightweight and portable inverter generators for travel and recreational activities.



Added benefits



Quieter*
Consistent, quiet power that traditional camping generators can't match



Lighter*
For easy mobility



Inverter technology
Produces smoother power¹ for sensitive electronics



Powersmart mode
Automatically adjusts engine speed to save fuel and run longer



Series	P2400 PowerSmart™ Series
Model #	030802
Running Watts ¹	1800
Starting Watts ²	2400
Phase/Voltage	1PH/230
Engine	
CC	79
Outlets	
	2 x 230V, 15A
	1x 12V, 5A - Regulated
	2x USB
Dimensions (L x W x H)	50.9 cm x 31.1 cm x 44.1 cm
Weight	22.7 kg
Limited Warranty ⁴	3 Years Consumer 1 Year Commercial

Features	
Fuel Tank Capacity	3.8 Litres
Decibel Rating (25% load/Rated load) ³	58/65
Alternator	Permanent Magnet
Starting	Pull Start
Low Oil Shutdown	✓
Protected Outlet Covers	✓
Automatic Idle Control	✓
Muffler (Spark Arrester Type)	Standard
Hour Meter	-
Fuel Gauge	-
LCD StatStation™	-
Wheels	-



Series	P3400 PowerSmart™ Series
Model #	030808
Running Watts ¹	2800
Starting Watts ²	3400
Phase/Voltage	1PH/230
Engine	
CC	171
Outlets	
	2 x 230V, 15A
	1x 12V, 5A - Regulated
	1x USB
Dimensions (L x W x H)	66 cm x 35.2 cm x 51.7 cm
Weight	38.6 kg
Limited Warranty ⁴	3 Years Consumer 1 Year Commercial

Features	
Fuel Tank Capacity	5.7 Litres
Decibel Rating (25% load/Rated load) ³	58/67
Alternator	Permanent Magnet
Starting	Pull Start
Low Oil Shutdown	✓
Protected Outlet Covers	✓
Automatic Idle Control	✓
Muffler (Spark Arrester Type)	Standard
Hour Meter	✓
Fuel Gauge	✓
LCD StatStation™	✓
Wheels	6"



Series	P4500 PowerSmart™ Series
Model #	030807
Running Watts ¹	3700
Starting Watts ²	4500
Phase/Voltage	1PH/230
Engine	
CC	224
Outlets	
	2 x 230V, 15A
	1x 12V, 5A - Regulated
	2x USB
Dimensions (L x W x H)	62.2cm x 44.7cm x 51.6cm
Weight	47 kg
Limited Warranty ⁴	3 Years Consumer 1 Year Commercial

Features	
Fuel Tank Capacity	13.2 Litres
Decibel Rating (25% load/Rated load) ³	61
Alternator	Permanent Magnet
Starting	Electric / Pull Start
Low Oil Shutdown	✓
Protected Outlet Covers	✓
Automatic Idle Control	✓
Muffler (Spark Arrester Type)	Standard
Hour Meter	Via mobile app InfoHub™
Fuel Gauge	✓
InfoHub	✓
Wheels	6"



3
Consumer
Limited
Warranty⁴



1
Commercial
Limited
Warranty⁴

* Compared to a traditional generator

¹ Per CSA C22.2 No. 100-14.

² Starting Watts reflects the maximum current that can momentarily be supplied when starting a motor, multiplied by the generator's rated voltage.

³ At 7m from control panel side.

⁴ See www.briggsandstratton.com for warranty details.

Briggs & Stratton has a policy of continuous product improvement and reserves the right to modify its specifications at any time and without prior notice. Product may vary from images shown.

Copyright ©2020. All rights reserved.



YOU. POWERED.