

HOME / SOLAR OFF GRID GENERATORS

MX11000IS 10500W Electric Start Digital Inverter Generator

**Quiet and powerful.
Portable and lightweight.**

When the power goes out, keeping essential lights on and the television running can make all the difference - especially when keeping the family calm and entertained.

Our home backup generators are designed for easy setup, quiet operation, and dependable performance when you need it most.

We've identified the key features to consider when choosing the right generator for your home, so you can feel confident and prepared - no matter the outage.



TECHNICAL INFORMATION

Voltage:	240V
Amperage:	39.6A
Displacement:	550cc
Engine Speed:	Variable
Outlets:	1 x 15A IP66 / 1 x 32A IP66
Rated Power:	9500W
Max Power:	10500W
Starting Method:	Recoil / Electric / Remote Control / 2 Wire Auto Start
Noise Level:	68dB
Fuel Tank:	30L
Rated Frequency:	50Hz
Battery:	12V 10Ah Lead Acid
Fuel Running Time @ 50% Load:	10.5 hours
Fuel Running Time @ 100% Load:	5.5 hours
Generator Dimensions (LxWxH):	810 x 600 x 695mm
Net Weight:	103kg

