

## **2000W PURE SINE WAVE DIGITAL INVERTER GENERATOR**

PORTABLE & LIGHT WEIGHT | LOW NOISE 59DB | 2.1 AMP USB OUTPUT **ECONOMY LOW IDLE SETTING** 

Smart Engine Control reduces engine speed depending on size of load for better fuel efficiency

- > Digital Inverter Technology
- > Pure Sine Wave Power for Sensitive Electronic
- > Appliances / Devices
- > Parallel Connection Cable Included
- > Low Noise 59dB
- > 5V 2.1 Amp USB Charging
- > Engine Smart Control Reduces Engine Speed Depending on Size of Load for Fuel Efficiency







PARALLEL CAPABLE

Voltage (V)	240V
Amperage (A)	6.7A
Displacement (cc)	79.8cc
Fuel Tank Capacity (L)	4L
Rated Power (Watts)	1600W
Max. Power (Watts)	2000W

Noise Level (dB's) at 7m	59
Weight (Net)	21kg
Ignition	Manual Recoil
Rated Frequency	50Hz
Cont. Running Time @50% Load	6.5 hrs
Cont. Running Time @100% Load	4 hrs



Barcode: 9356905000050