

MX7000ES

7KVA PETROL GENERATOR

4 STAGE DIGITAL METER | AUTOMATIC VOLTAGE REGULATOR
SUPERIOR QUALITY SENCI ALTERNATOR

- > Electric Starting System (Battery Included)
- > 4 Stage Digital Meter Display
- > Automatic Voltage Regulator
- > Low Oil Alert Sensor
- > Superior Quality SENCI Alternator
- > 40L Large Capacity Fuel Tank
- > Large Muffler Design to reduce Noise
- > Heavy Duty 32mm Frame with Wheels and Handle



**ELECTRIC/RECOIL
STARTING METHOD**



Voltage (V)	240V
Amperage (A)	20.8A
Displacement (cc)	389cc
Fuel Tank Capacity (L)	40L
Rated Power (Watts)	6.2kVA/5000W
Max. Power (Watts)	7kVA/5500W

Noise Level (dB's) at 7m	82
Weight (Net)	85kg
Ignition	Electric/Recoil
Rated Frequency	50Hz
Cont. Running Time @50% Load	17.5 hrs
Cont. Running Time @100% Load	14 hrs

2
YEAR
WARRANTY